

AAP 5500



Frekans	Hz	50
Jeneratör Modeli		AAP 5500
DY]b:]nUhi	TL	2040

x N9 @@? @F



M5? #; x GH9F ; 9G
? U'Ub'nU_iha]Ufibib[" n'Yba Yg]b]gU 'Untub'XYdc
" nYf]bXY_][" gYf[Y



C < J 'A CHCF
6U_ia 'j Y_'j 'Ubia i'XU'U'_c'Um' gH'Yb'gi dUd'i'a c'cf



M5 '5@5FA =
A c'cf'nU_gin'_U'Xi 'ibXU', U'i 'a Ugibi'" b'YnYfY_'a c'cfi
_cfi n'ub'U'Ufa 'g]gY'a]



5J F
J c'U'ib'&&\$'j 'j YnU"', \$'J 'fXU'gU]hc'UfU'_U'a Ugibi
gU 'Untub'c'ca Uf_]j c'U'^fY[" 'U'f'f



H9? 9F @9? 'J 9 H5 'A 5'G GH9A
HU_ia UXU'_c'Um'_gU 'Untub'&UXYh'Y_YFY_'fY'b'j Y'h'fa U
_c'i bXUb'c'i Ub'gYh



5 'ifi'_U_ia ; Y_]X]]bXY'XYj fYm'_YgYfY_'YbYfU'f'
_cfi n'ub' U'Yf



J C @HA 9HF 9
; fi d' nYf]bXY'5"7"u'i_j c'U'ib'ib[" gH'YfYb'_UXfUb



> ? @9'G GH9A
'_ ; U'i 'h'fa UXU'j YnU'gc_i '_\Uj U'UfXU'_c'Um, U'i 'h'fa U
Ua U, 'iznYb[]b'mU'ih_U'f'ia 'i'gU 'Untub'g]gY'a



u : H'9@9A 5B @=< 5J 5 : @HF 9G
9a]Yb'\Uj Ubib'hc'n'j Y'd]g]_YfXy'b'U'fiba Ugibi'gU 'Untub'
,]znY'Ya Ub'i'\Uj U'z'fYg]



6y My? 'M5? #H5B? =
% ! &) 'h'U'fU'gi'mU'ih'U'ub'_i

AAP 5500

● JENERATÖR

AC Nominal Güç	kW	4,00
	kVA	5,00
Maksimum Güç	kW	4,50
	kVA	5,50
57 'Bca]bU'5_ia	57 'Bca]bU'5_ia	17,30
Voltaj	V	230
Frekans	Hz	50
: Un'GUmgj		1
Güç Faktörü		0,80
MU_ihH' _Yfja]	L/sa	2,50
G' fy_]uU' a U	Saat	10,00
Gürültü Seviyesi	dB(A)	72,00

● MOTOR

Devir	d/dk	3000
Güç	Hp	11,0
Silindir No.		1,0
Silindir Hacimi	mL.	337
MU_ihH' f'		Benzin
MU_? UdUg]fYg]	L	1,1
MU_ihHUb_? UdUg]fYg]	L	25,0
GUfhi Y_]		d]

● BOYUT

En	mm.	695
Boy	mm.	555
Yükseklik	mm.	580
5 ifi_	kg.	78,0